

# Sigma XT



### **Product Overview**

- O Designed and manufactured to the highest standards in a quality controlled environment and with European EN12094-1 approvals, the Sigma XT extinguishant releasing panel offers outstanding value and performance for all small to medium fixed firefighting installations.
- O With three detection zones as standard, extinguishant release can be configured to activate from any combination of detection zone inputs to allow (among other combinations) any two from three type activations such as would be required for detection in ceiling void, room and floor void applications.
- ☐ The extensive configuration options of the Sigma XT allow the functionality of the system to be extensively modified while still complying with the requirements of the controlling standard for the equipment (EN12094-1, EN54-2 and EN54-4).
- O The panel contains a large LED display to enable easy configuration and control which also displays the time remaining until extinguishant release for added user safety.
- O The countdown timer is duplicated on up to seven remote status units to provide local indication of the extinguishant system status.
- O With all of the electronics mounted on a single, easily removable, steel plate Sigma XT panels are both robust and easy to install.
- O Sigma XT is supplied in an enclosure that matches the design and colour of the Sigma CP range.

## **Extinguishant Control Panel**

#### **Features**

- Approved to EN12094-1, EN54-2 and EN54-4
- Three detection zones as standard
- Any single zone or any combinations of zones can be configured to release
- O Configurable first stage sounder delays
- Configurable detection delays
- Zero time delay upon manual release option
- Compatible with I.S. barriers
- Non-latching zone input option to receive signals from other systems such as aspirating equipment
- Configurable extinguishant delays up to 60 seconds in 5 second steps
- Configurable extinguishant duration up to 5 minutes in 5 second
- Countdown timer shows time remaining until release
- Supports up to seven, four wire status indicators
- Built in Extract Fan control

## **Programmable Functions**

#### Access Level 2

- Test Zones 1 to 3
- Disable Zones 1 to 3
- Disable 1st Stage Alarms
- Disable Pre-activated 1st Stage Relay
- Disable Pre-activated 2nd Stage Relay
- Disable Extract Fan Output
- Disable Manual Release Input
- Disable Extinguishant Sub System
- Activate Extract Fan Output Activate Alarm Delays

#### Access Level 3

- Sounder Delay
- Coincidence Detection Disable Panel Features
- Zone Alarm Delays (Detectors) Zone Alarm Delay (Call Points)
- Configure Zone for I.S Barrier Use
- Zone Short Circuit Alarm
- Zone Non Latching
- Zone Inputs Delay
- Extinguishant Release Time Delay Extinguishant Release Duration Timer
- Extinguishant Reset Delay Timer

### **Panels**

**Product Code** Description Size (mm)

K11031M2 Surface mounting panel 385 x 310 x 90

## **Technical**

Construction IP Ratino

**ROV** output

**Finish** 

Colour - lid & box BS 00 A 05 grey - fine texture RAL 7047 light grey - satin Colour - controls plate & labels

Weight 6ka 230V AC +10%/-15% (100 Watts maximum) 1.6 Amp (F1.6A L250V)

Mains supply Mains supply fuse Power supply rating

Quiescent current of panel in mains fail

3 Amps total including battery charge 28V +/- 2V Maximum ripple current 200 millivolts Battery type (Yuasa NP) Two 12 Volt 7Ah sealed lead acid in series

**Battery charge voltage** 27.6VDC nominal (temperature compensated)

1.2mm mild sheet steel

Epoxy powder coated

Fused at 500mA with electronic fuse

IP30

0.095A

**Battery charge current** 0.7A maximum **Battery** fuse 20mm, 3.15A glass Maximum current draw from batteries 3 Amps

Sounder outputs 24V Fused at 500mA with electronic fuse Fault relay contact rating 30VDC 1A Amp maximum Fire relay contact rating 30VDC 1A Amp maximum Local fire relay contact rating 30VDC 1A Amp maximum First stage contact rating 30VDC 1A Amp maximum Second stage contact rating 30VDC 1A Amp maximum **Extract contact rating** 30VDC 1A Amp maximum

Zone quiescent current 2mA maximum

Terminal capacity 0.5mm<sup>2</sup> to 2.5mm<sup>2</sup> solid or stranded wire Number of detectors per zone Dependent on type (maximum 32)

Number of sounders per circuit Dependent on type (max. 0.5A per sounder circuit)

Detection circuit end of line 6K8 5% 1/2 Watt resistor Monitored input end of line 6K8 5% 1/2 Watt resistor 10K 5% ¼ Watt resistor Sounder circuit end of line Extinguishant output EOL 1N4004 Diode

No. of detection circuits

No. of sounder circuits 2 x 1st Stage, 1 x 2nd Stage

Extinguishant release output Fused at 1 Amp

Adjustable 0 to 60 seconds (in 5 second steps) Extinguishant release delay Extinguishant release duration Adjustable 60 to 300 seconds (in 5 second steps) SIL, AL, FLT, RST inputs Switched -ve, max resistance 100 Ohms

8K ohms to 1K ohm Zone normal threshold 999 ohms to 400 ohms Detector alarm threshold 399 ohms to 100 ohms Call point alarm threshold Short circuit threshold 99 ohms to 0 ohms Head removal condition 15.5 to 17.5 volts Cabling FP200 or equivalent Monitored inputs normal threshold 8K ohms to 1K ohm

Monitored inputs alarm threshold 999 ohms to 100 ohms Monitored inputs Short circuit threshold 99 ohms to 0 ohms Status unit/Ancillary board connection Two wire RS485 connection

Status unit power output Fused at 500mA with electronic fuse

1st Stage Sounders 0-470R O-470R 6KB S O L olololo To Status Units Auxiliary Signalling Relays واواواو LERONIGIL ALFLITSTIJE - 1,12 - 1,12 - 1,12 - 1,14 -Sigma XT PCB